

POWER ANALYZER

Model : DW-6090

ISO-9001, CE, IEC1010



FEATURES



- * Multi-functions : WATT, VA, Whr, PF (Power factor), ACV, ACA, DCV, DCA, Hz, ohm.
- * True AC power(Watt) & apparent power (VA) measurement.
- * True rms display for ACV, ACA.
- * Supper large LCD, display the Watt, Power factor, Voltage & Current value at the same time.
- * Accept inductive clamp or CT input.
- * Peak hold & data hold function.
- * Hi, low alarm setting, RS-232/

LUTRON ELECTRONIC

POWER ANALYZER, Model : DW-6090

FEATURES

* Multi-functions : WATT, VA, Whr, Power factor ACV, ACA, DCV, DCA, Hz, ohm.	* Alarm Hi, low setting capability.
* True AC power measurement, not apparent power.	* RS-232 output interface.
* True rms display for ACV, ACA.	* Exclusive custom exclusive design LSI circuit, provides high accuracy, reliability and durability.
* Super large LCD, easy to read-out, display the Watt, Power factor, Voltage & Current value at the same time.	* Built-in over input indication.
* Current mode from direct input, inductive clamp probe or CT.	* Power supply by DC battery or AC to DC adapter.
* Auto range.	* Built-in low battery indicator.
* Built-in peak hold & data hold function.	* Durable bench type housing plastic case with carrying handle.

GENERAL SPECIFICATIONS

Display	* 93 mm x 52 mm large LCD (Liquid Crystal Display) display panel.. * Multi-display unit, show Volt, Ampere, Watt, Power factor at same time.	Data Output Sampling Time Operating Temp. Operating Humidity	RS232 serial interface. W, A, V - 1.5 sec. DCV, DCA - 1 sec. 0 to 50°C (32 to 122 °F). Less than 80 % R.H..
Measurement	WATT, VA, Whr., Power factor ACV, ACA, DCV, DCA, Hz, ohm.	Power Supply Power Consumption	DC 9V, 1.5 V AA (UM-3) battery x 6 PCs. Approx. DC 30 mA
Zero Adjustment	Watt : External adjustment. DCV, ACV, DCA, ACA: Automatic adjustment.	Dimension	280 x 210 x 90 mm (11.0 x 8.3 x 3.5 inch).
Polarity	Automatic switching, "-" indicates reverse polarity.	Weight	Approx. 1,100 g (2.4 LB).
Current input mode	Direct input, inductive clamp probe or CT.	Standard Accessories	Test lead(red & black).....1 pair. Instruction Manual.....1 PC.
Over input Indication	Indication of " - - - " or " - - - .		

ELECTRICAL SPECIFICATIONS (23± 5 °C)

Watt (AC, true power), current mode from direct input.

Range	Resolution	Accuracy	Remark
1 Watt to 9,999 Watt	1 Watt	± (1.5 % + 1 d)	* Auto range. * Frequency Characteristic: 45 Hz-65Hz. * Accuracy is specified under input signal frequency of 50/60 Hz.
10 K Watt to 99.99 K Watt	10 Watt		

Watt (AC, true power), current from inductive probe or CT.

Range	Resolution	Accuracy	Remark
1 Watt to 9,999 Watt	1 Watt	± (1.5 % + 1 d)	* Auto range.
10 KW to 99.99 KW	10 Watt		* Frequency Characteristic: 45 Hz-65Hz.
100.0 KW to 999.9 KW	0.1 kW		* Accuracy is specified under input signal frequency of 50/60 Hz.
1000 KW to 1999 KW	1 kW		

VA (AC), current mode from direct input

Range	Resolution	Accuracy	Remark
0.01 VA to 99.99 VA	0.01 VA	± (1.5 % + 1 d)	* Auto range.
100.0 VA to 999.9 VA	0.1 VA		* Frequency Characteristic: 45 Hz-65Hz.
1000 VA to 9999 VA	1 VA		* Accuracy is specified under input signal frequency of 50/60 Hz.
10.00 K VA to 39.99 KVA	10 VA		

POWER FACTOR, current mode from direct input only

Range	Resolution	Accuracy
0.01 to 1.00	0.01	± (1.5 % + 2 d)

AC VOLTAGE, DC VOLTAGE

Range	Resolution	Accuracy	Input Impedance	Overload circuit Protection
0.1 V to 299.9 V	0.1 V	± (1 % + 1 d)	10 Mega ohm	AC 700 V
300 V to 600 V	1 V			DC 1000 V

Remark : Auto range.

AC CURRENT, DC CURRENT, current mode from direct input

Range	Resolution	Accuracy	Voltage drop (in case of full scale)
0.01 A to 20.00 A	10 mA	± (1 % + 1 d)	2 V AC

* ACA, ACV frequency characteristic : 45 Hz to 65 Hz, specification be tested on sine wave of 50/60 Hz.

* Converter response : Average responding, calibrated to display RMS value of sine wave.

AC CURRENT, DC CURRENT, current mode from inductive probe

Range	Resolution	Accuracy	Remark
1 A to 1000 A	1 A	± (1 % + 1 d)	ACA : 1 AC mV per 1 AC ampere. DCA : 1 DC mV per 1 DC ampere.

AC CURRENT, current mode from CT (current transformer)

Range	Resolution	Accuracy	Remark
CT 100/5A, 0.1 - 100.0 A	0.1 A	Depend the CT its own	
CT 1000/5A, 1 - 1000 A	1 A	accuracy.	

Watt Hour, current from direct input

Range	Resolution	Accuracy	Remark
0.001 Whr to 9,999 Whr	0.001 Whr		* Auto range.
10.00 Whr to 99.99 Whr	0.01 Whr	± (1 % + 1 d)	* Frequency Characteristic: 45 Hz-65Hz. * Accuracy is specified under input signal frequency of 50/60 Hz.
100.0 Whr to 999.9 Whr	0.1 Whr		
1000 Whr to 9999 Whr	1 Whr		
10 K Whr to 99.9 K Whr	10 Whr		
100 K Whr to 999.9 K Whr	100 Whr		
1000 K Whr to 9999 K Whr	1 K Whr		

OHMS

Range	Resolution	Accuracy	Overload Circuit Protection
1 ohm to 9,999 ohm	1 ohm	± (1 % + 1 d)	AC/DC 400V
10 K ohm to 19,99 K ohm	10 ohm		

Hz

Range	Resolution	Accuracy	Overload Circuit Protection
10.0 Hz to 99.9 Hz.	0.1 Hz	± (1 % + 1 d)	
100 Hz to 999 Hz.	1 Hz		

* Appearance and specifications listed in this brochure are subject to change without notice.

0405-DW6090